

Effortless Control



**The CP20xt and CP20 =
The very latest in a range of
high performance
lighting control
and effects products**

With some lighting consoles you could spend hours just trying to get a fixture to acknowledge your presence. Then again, you could get the very latest lighting console from **Elektralite** and spend hours creating fantastic effects instead. The CP20xt / CP20 comes equipped with the kind of features you would expect to find on consoles three times the price: Control of up to 24 / 24 fixtures; fixture library; preset focuses; hot keys / instant access; floppy disk drive for data saves and OS updates and much more. Do yourself a favour...call for details.



model n° C P 20 x t

CP20xt and CP20 Specification



w
model n° C P 20
h
d

- DMX controller for both moving fixtures and conventional dimmers.
- Hot keys for instant access to fixtures, cues, chases and macros.
- Instant access to individual features such as color and gobos.
- Instant access to any special features such as rotating prisms.
- Movement control through on-board joystick or external outboard device (such as mouse, trackball or touch-pad).
- Fine and coarse control.
- Large easy to read display.
- 24 channels per fixture.
- 24 fixtures maximum.
- Control of all 512 DMX channels.
- Softpatch capability for channel patching board to output.
- 96 positional focuses.
- Audio input with tempo adjust button.
- 8 Sub-masters with flash bump buttons for hands-on control.
- 960 Cues, 96 Chases and 48 Macros.
- Cues can have variable timed cross-fades while chase speeds are fully variable.
- Macros can be time varied on a step by step basis.
- Library of fixtures. Ability to 'make-your-own' fixture or customization of fixtures.
- Software upgrades can be downloaded from the web and uploaded into the board.
- 3 pin XLR connector for CAE Littlite.
- CP20 programming style is similar to CP10xt.
- Available as CP20, a 19" rack mounting unit or in console format as CP20xt
- Backup of board through optional outboard 3.5" disk drive (disk drive can also be used with CP10xt) or internal 3.5" drive on CP20xt.
- 3 and 5 pin XLRs for DMX512 output.
- Weights & Dimensions: CP20 w19" (48.26cm), h15.75" (40cm), d6" (12.7cm) weight 12.18lbs (5.52 kg) w/o PSU. CP20xt w25.75" (65.40cm), h18.25" (46.35cm), d6"max., weight 21lbs (9.52kg) w/o PSU.

Telephone +1 631 249 3662 **Elektralite** is a division of
 Facsimile +1 631 753 1020 Group One Limited
 Email info@MyElektralite.com 200 Sea Lane Farmingdale
 Web www.MyElektralite.com New York 11735 USA